

Cleaner 14



Product

Simson Cleaner 14 is a thin liquid product for cleaning and degreasing substrates before sealing or bonding with specific Simson products. Consult the Technical Data Sheet of the particular product.

Applications

- Cleaning and degreasing of closed substrates.
- Removing uncured sealant- and adhesive remains on substrates and tools.

Method of use

Substrates must be dry. Firmly rub the substrates with a clean, colourless cloth or tissue paper wetted with Cleaner 14. In case the substrate is strongly contaminated repeat this once more. Replace the cloth when it becomes dirty. Avoid contamination in the tin. Always close the tin immediately after use. Only pre-treat as much surfaces that can be sealed or bonded within 6 hours.

Application temperature: Between +5°C and +30°C.

Drying time: After a drying time of 5 minutes the sealant or adhesive can be applied.

Note: It is recommended to carry out a trial in advance on a small piece to check whether the substrate will be affected by Cleaner 14. Plastics and lacquers can especially be sensitive.

ADHESIVES AND SEALANTS

Cleaner 14

Technical data

Dry contents	0%
Specific gravity	0.8 g/ml
Flashpoint	-6°C
Colour	transparent
Packaging	1 litre tin

Storage stability

Cleaner 14 can be stored for at least 12 months in an original, unopened container in a dry place at temperatures between +5°C and +30°C.

Further information

The following publication is available on request:

- Material Safety Data Sheets (MSDS)

UK

Bostik Ltd.
Stafford
Tel: +44 (0) 1785 27 27 27
Fax: +44 (0) 1785 22 26 65

France

Bostik S.A.
Paris
Tel: +33 (0) 1 74 96 91 18
Fax: +33 (0) 1 47 96 94 20

Germany

Bostik GmbH
Borgholzhausen
Tel: +49 (0) 54 25/8 01-0
Fax: +49 (0) 54 25/80 11 40

The Netherlands

Bostik B.V.
's-Hertogenbosch
Tel: +31 (0) 73 6 244 244
Fax: +31 (0) 73 6 244 344

For more Bostik locations please consult www.bostik.com

**Bostik**
The Adhesive Company

All figures, recommendations and safety precautions are based on thorough investigations and our actual experience and are without engagement. Although the documentation has been set up with most carefulness, we do not accept any responsibility for mistakes, inaccuracies or printer's errors. We reserve the right to adjust the product, whenever we feel necessary. Because the design, the quality of the substrate and the conditions during application fall beyond our control, no responsibility for executed works can be accepted on the basis of this documentation. We therefore recommend to carry out own tests on the spot. All our sales and deliveries are subject to our general sales- and delivery conditions.